

| | |
|------------|-----------------|
| Datum | 22.10.13 |
| Projektnr. | |
| Sachbearb. | Daniel Lenhardt |
| Seite | 1 |

| Country | Status | Frequency in MHz | Power | Technique | Comments |
|------------------------|--------|------------------|-----------|-----------|---|
| Albania | NA | | | | |
| Algeria | NA | | | | |
| Argentina | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Armenia | OK | 865.6 - 867.6 | | ETSI | |
| Australia | OK | 920 - 926 | 4 W EIRP | | |
| | | 918 - 926 | 1 W EIRP | | |
| Austria | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Azerbaijan | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Bahrain | NA | | | | |
| Bangladesh | NA | | | | |
| Belarus | OK | 865.6 - 867.6 | 2 W ERP | ETSI | Under License. The assignment of radio frequencies or channels should to be performed in established order. |
| Belgium | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Bolivia | NA | | | | |
| Bosnia and Herzegovina | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Botswana | NA | | | | |
| Brazil | OK | 902 - 907.5 | 4 W EIRP | FHSS | |
| | | 915 - 928 | 4 W EIRP | FHSS | |
| Brunei Darussalam | OK | 866 - 869 | 0.5 W ERP | | License free |
| | | 923 - 925 | 2 W ERP | | Supports EN 302 208, EN 300 220-1 and FCC part 15 |
| Bulgaria | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Cambodia | NA | | | | |
| Cameroon | NA | | | | |
| Canada | OK | 902-928 | 4 W EIRP | FHSS | |
| Chile | OK | 902-928 | 4 W EIRP | FHSS | |
| China | OK | 920.5 - 924.5 | 2 W ERP | FHSS | |
| Colombia | OK | 902-928 | 4 W EIRP | FHSS | |
| Congo, Rep. | NA | | | | |
| Costa Rica | OK | 902-928 | 4 W EIRP | FHSS | |
| Côte d'Ivoire | NA | | | | |
| Croatia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Cuba | NA | | | | |
| Cyprus | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Czech Republic | OK | 865.6 - 867.7 | 2 W ERP | ETSI | |
| Denmark | OK | 865.6 - 867.8 | 2 W ERP | ETSI | |
| Dominican Republic | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Ecuador | NA | | | | |
| Egypt, Arab Rep. | WiP | | | | |
| El Salvador | NA | | | | |
| Estonia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Finland | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| France | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Georgia | NA | | | | |

| | |
|------------|-----------------|
| Datum | 22.10.13 |
| Projektnr. | |
| Sachbearb. | Daniel Lenhardt |
| Seite | 2 |

| Country | Status | Frequency in MHz | Power | Technique | Comments |
|--|--------|---|--------------------------------------|---|--|
| Germany | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Ghana | NA | | | | |
| Greece | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Guatemala | NA | | | | |
| Honduras | NA | | | | |
| Hong Kong, China | OK | 865 - 868 920 - 925 | 2 W ERP 4 W EIRP | | |
| Hungary | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Iceland | Ok | 865.6 - 867.6 | 2 W ERP | ETSI | |
| India | OK | 865 - 867 | 4 W ERP | | |
| Indonesia | Ok | 923 - 925 | 2 W ERP | | |
| Iran, Islamic Rep. | Ok | 865 - 868 | 2 W ERP | ETSI | |
| Ireland | Ok | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Israel | Ok | 915 - 917 | 2 W ERP | | New regulations agreed on 27.08.2012 limit Out of Band (OoB) emissions; restrictions on duty cycle relax OoB linearly at 915 MHz. |
| Italy | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Jamaica | NA | | | | |
| Japan (effective until March 31, 2018) | OK | 952 - 956.4 952 - 956.4 952 - 957.6 | 4 W EIRP 0.5 W EIRP 20 mW EIRP | Either LBT free with 4 x 200KHz channels for readers or LBT LBT LBT | License required for using 952-956.4 MHz up to 4W EIRP License required for using 952-956.4 MHz up to 0.5 W EIRP 952-957.6 MHz available for unlicensed use up to 20 mW EIRP |
| Japan (effective as of July 25, 2012) | OK | 916.7 - 920.9 916.7 - 923.5 | 4 W EIRP 0.5 W EIRP | Either LBT free or LBT LBT | License required for using 916.7-920.9 MHz up to 4 W EIRP Channel bundle is allowed in 920.3- 920.9MHz 916.7-923.5 MHz available for unlicensed use up to 0.5 W EIRP |
| Jordan | OK | 865 - 868 | 2.0 W ERP | | |
| Kazakhstan | NA | | | | |
| Kenya | NA | | | | |
| Korea, Rep. | OK | 917 - 920.8 917 - 923.5 | 4 W EIRP 200 mW EIRP | FHSS or LBT | |

| | |
|------------|-----------------|
| Datum | 22.10.13 |
| Projektnr. | |
| Sachbearb. | Daniel Lenhardt |
| Seite | 3 |

| Country | Status | Frequency in MHz | Power | Technique | Comments |
|-----------------|--------|--------------------------|----------------------|-----------|--|
| Korea (DPR) | NA | | | | |
| Kuwait | NA | | | | |
| Kyrgyz Republic | NA | | | | |
| Latvia | OK | 865.6 - 867.6 | 2 W ERP | LBT | |
| Lebanon | NA | | | | |
| Libya | NA | | | | |
| Lithuania | OK | 865.6 - 867.6 | 2 W ERP | ETSI | Individual licence required. |
| Luxembourg | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Macao, China | NA | | | | |
| Macedonia, FYR | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Malaysia | OK | 919 - 923 | 2 W ERP | | Authorization for ERP below 2W is by way of Class Assignment (CA) and up to 4W is by way of an Apparatus Assignment (AA). The use of equipment exceeding 4W is not permitted. The use of spectrum under CA does not require an application to MCMC but for AA, an application is required. |
| Malta | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Mauritius | NA | | | | |
| Mexico | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Moldova | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Mongolia | NA | | | | |
| Montenegro | NA | | | | |
| Morocco | NA | | | | |
| Netherlands | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| New Zealand | OK | 864 - 868 921.5 - 928 | 6 W EIRP | FHSS | |
| Nicaragua | NA | | | | |
| Nigeria | NA | | | | |
| Norway | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Oman | OK | 865.6 - 867.7 | 2 W ERP | ETSI | |
| Pakistan | WiP | 865 - 868 | 0.1 W ERP | | |
| Panama | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Paraguay | NA | | | | |
| Peru | OK | 915 - 928 916 - 928 | 1 W EIRP 4 W EIRP | FHSS | Ministry must be informed. |
| Philippines | WiP | 918 - 920 | 0.5 W ERP | | |
| Poland | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Portugal | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Romania | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |

| | |
|------------|-----------------|
| Datum | 22.10.13 |
| Projektnr. | |
| Sachbearb. | Daniel Lenhardt |
| Seite | 4 |

| Country | Status | Frequency in MHz | Power | Technique | Comments |
|--------------------|--------|------------------|------------|--|---|
| Russian Federation | OK | 865.6 - 867.6 | 100 mW ERP | ETSI | Under License. The assignment of radio frequencies or channels is not required when using inside the boundaries of the airports and with a mandatory requirement for a Listen Before Talk (LBT) mechanism. |
| | | 866 - 868 | 500 mW ERP | | |
| | | 866.0 - 867.6 | 2 W ERP | | |
| | | 916 - 921 | 1 W ERP | Channel spacing: 1.2 MHz Center frequencies: 916.2, 917.4, 918.6, 919.8 MHz | |
| | | | | | Additional regulation from March 2011. Under License. It is prohibited to use interrogators outside buildings. Permission to use the radio frequencies by active RFID interrogators and the registration of the active interrogator are required. |
| Saudi Arabia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Senegal | NA | | | | |
| Serbia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Singapore | OK | 866 - 869 | 0.5 W ERP | | |
| | | 920 - 925 | 2 W ERP | | |
| Slovak Republic | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Slovenia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| South Africa | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| | | 915.4 - 919 | 4 W EIRP | FHSS | |
| | | 919.2 - 921 | 4 W EIRP | Non-modulating | |
| Spain | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Sri Lanka | NA | | | | |
| Sudan | NA | | | | |
| Sweden | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Switzerland | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Syrian Arab Rep. | NA | | | | |

| | |
|------------|-----------------|
| Datum | 22.10.13 |
| Projektnr. | |
| Sachbearb. | Daniel Lenhardt |
| Seite | 5 |

| Country | Status | Frequency in MHz | Power | Technique | Comments |
|----------------------|--------|------------------|-----------|--|--|
| Taiwan | OK | 922 - 928 | 1 W ERP | FHSS | Indoor |
| | | 922 - 928 | 0.5 W ERP | | Outdoor |
| Tajikistan | NA | | | | |
| Tanzania | NA | | | | |
| Thailand | OK | 920 - 925 | 4 W EIRP | FHSS | New regulations effective since 20 January 2006. License required for power above 0.5 W. |
| Trinidad and Tobago | NA | | | | |
| Tunisia | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| Turkey | OK | 865.6 - 867.6 | 2 W ERP | ETSI | Indoor use only |
| Turkmenistan | NA | | | | |
| Uganda | NA | | | | |
| Ukraine | NA | | | | |
| United Arab Emirates | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| United Kingdom | OK | 865.6 - 867.6 | 2 W ERP | ETSI | |
| United States | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Uruguay | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Uzbekistan | NA | | | | |
| Venezuela, RB | OK | 902 - 928 | 4 W EIRP | FHSS | |
| Vietnam | OK | 866 - 869 | 0.5 W ERP | Licence required for power above 0.5 W ERP Licence required for power above 0.5 W ERP | |
| | | 920 - 925 | 2 W ERP | | |
| Yemen, Rep. | NA | | | | |
| Zimbabwe | NA | | | | |