

Datum	22.10.13
Projektnr.	
Sachbearb.	Daniel Lenhardt
Seite	1

Country	Status	Frequency in MHz	Power	Technique	Comments
Albania	NA				
Algeria	NA				
Argentina	OK	902 - 928	4 W EIRP	FHSS	
Armenia	OK	865.6 - 867.6		ETSI	
Australia	OK	920 - 926	4 W EIRP		
		918 - 926	1 W EIRP		
Austria	OK	865.6 - 867.6	2 W ERP	ETSI	
Azerbaijan	OK	865.6 - 867.6	2 W ERP	ETSI	
Bahrain	NA				
Bangladesh	NA				
Belarus	OK	865.6 - 867.6	2 W ERP	ETSI	Under License. The assignment of radio frequencies or channels should be performed in established order.
Belgium	OK	865.6 - 867.6	2 W ERP	ETSI	
Bolivia	NA				
Bosnia and Herzegovina	OK	865.6 - 867.6	2 W ERP	ETSI	
Botswana	NA				
Brazil	OK	902 - 907.5	4 W EIRP	FHSS	
		915 - 928	4 W EIRP	FHSS	
Brunei Darussalam	OK	866 - 869	0.5 W ERP		License free
		923 - 925	2 W ERP		Supports EN 302 208, EN 300 220-1 and FCC part 15
Bulgaria	OK	865.6 - 867.6	2 W ERP	ETSI	
Cambodia	NA				
Cameroon	NA				
Canada	OK	902-928	4 W EIRP	FHSS	
Chile	OK	902-928	4 W EIRP	FHSS	
China	OK	920.5 - 924.5	2 W ERP	FHSS	
Colombia	OK	902-928	4 W EIRP	FHSS	
Congo, Rep.	NA				
Costa Rica	OK	902-928	4 W EIRP	FHSS	
Côte d'Ivoire	NA				
Croatia	OK	865.6 - 867.6	2 W ERP	ETSI	
Cuba	NA				
Cyprus	OK	865.6 - 867.6	2 W ERP	ETSI	
Czech Republic	OK	865.6 - 867.7	2 W ERP	ETSI	
Denmark	OK	865.6 - 867.8	2 W ERP	ETSI	
Dominican Republic	OK	902 - 928	4 W EIRP	FHSS	
Ecuador	NA				
Egypt, Arab Rep.	WiP				
El Salvador	NA				
Estonia	OK	865.6 - 867.6	2 W ERP	ETSI	
Finland	OK	865.6 - 867.6	2 W ERP	ETSI	
France	OK	865.6 - 867.6	2 W ERP	ETSI	
Georgia	NA				

Datum	22.10.13
Projektnr.	
Sachbearb.	Daniel Lenhardt
Seite	2

Country	Status	Frequency in MHz	Power	Technique	Comments
Germany	OK	865.6 - 867.6	2 W ERP	ETSI	
Ghana	NA				
Greece	OK	865.6 - 867.6	2 W ERP	ETSI	
Guatemala	NA				
Honduras	NA				
Hong Kong, China	OK	865 - 868 920 - 925	2 W ERP 4 W EIRP		
Hungary	OK	865.6 - 867.6	2 W ERP	ETSI	
Iceland	Ok	865.6 - 867.6	2 W ERP	ETSI	
India	OK	865 - 867	4 W ERP		
Indonesia	Ok	923 - 925	2 W ERP		
Iran, Islamic Rep.	Ok	865 - 868	2 W ERP	ETSI	
Ireland	Ok	865.6 - 867.6	2 W ERP	ETSI	
Israel	Ok	915 - 917	2 W ERP		New regulations agreed on 27.08.2012 limit Out of Band (OoB) emissions; restrictions on duty cycle relax OoB linearly at 915 MHz.
Italy	OK	865.6 - 867.6	2 W ERP	ETSI	
Jamaica	NA				
Japan (effective until March 31, 2018)	OK	952 - 956.4 952 - 956.4 952 - 957.6	4 W EIRP 0.5 W EIRP 20 mW EIRP	Either LBT free with 4 x 200KHz channels for readers or LBT LBT LBT	License required for using 952-956.4 MHz up to 4W EIRP License required for using 952-956.4 MHz up to 0.5 W EIRP 952-957.6 MHz available for unlicensed use up to 20 mW EIRP
Japan (effective as of July 25, 2012)	OK	916.7 - 920.9 916.7 - 923.5	4 W EIRP 0.5 W EIRP	Either LBT free or LBT LBT	License required for using 916.7-920.9 MHz up to 4 W EIRP Channel bundle is allowed in 920.3- 920.9MHz 916.7-923.5 MHz available for unlicensed use up to 0.5 W EIRP
Jordan	OK	865 - 868	2.0 W ERP		
Kazakhstan	NA				
Kenya	NA				
Korea, Rep.	OK	917 - 920.8 917 - 923.5	4 W EIRP 200 mW EIRP	FHSS or LBT	

Datum	22.10.13
Projektnr.	
Sachbearb.	Daniel Lenhardt
Seite	3

Country	Status	Frequency in MHz	Power	Technique	Comments
Korea (DPR)	NA				
Kuwait	NA				
Kyrgyz Republic	NA				
Latvia	OK	865.6 - 867.6	2 W ERP	LBT	
Lebanon	NA				
Libya	NA				
Lithuania	OK	865.6 - 867.6	2 W ERP	ETSI	Individual licence required.
Luxembourg	OK	865.6 - 867.6	2 W ERP	ETSI	
Macao, China	NA				
Macedonia, FYR	OK	865.6 - 867.6	2 W ERP	ETSI	
Malaysia	OK	919 - 923	2 W ERP		Authorization for ERP below 2W is by way of Class Assignment (CA) and up to 4W is by way of an Apparatus Assignment (AA). The use of equipment exceeding 4W is not permitted. The use of spectrum under CA does not require an application to MCMC but for AA, an application is required.
Malta	OK	865.6 - 867.6	2 W ERP	ETSI	
Mauritius	NA				
Mexico	OK	902 - 928	4 W EIRP	FHSS	
Moldova	OK	865.6 - 867.6	2 W ERP	ETSI	
Mongolia	NA				
Montenegro	NA				
Morocco	NA				
Netherlands	OK	865.6 - 867.6	2 W ERP	ETSI	
New Zealand	OK	864 - 868 921.5 - 928	6 W EIRP	FHSS	
Nicaragua	NA				
Nigeria	NA				
Norway	OK	865.6 - 867.6	2 W ERP	ETSI	
Oman	OK	865.6 - 867.7	2 W ERP	ETSI	
Pakistan	WiP	865 - 868	0.1 W ERP		
Panama	OK	902 - 928	4 W EIRP	FHSS	
Paraguay	NA				
Peru	OK	915 - 928 916 - 928	1 W EIRP 4 W EIRP	FHSS	Ministry must be informed.
Philippines	WiP	918 - 920	0.5 W ERP		
Poland	OK	865.6 - 867.6	2 W ERP	ETSI	
Portugal	OK	865.6 - 867.6	2 W ERP	ETSI	
Romania	OK	865.6 - 867.6	2 W ERP	ETSI	

Datum	22.10.13
Projektnr.	
Sachbearb.	Daniel Lenhardt
Seite	4

Country	Status	Frequency in MHz	Power	Technique	Comments
Russian Federation	OK	865.6 - 867.6	100 mW ERP	ETSI	Under License. The assignment of radio frequencies or channels is not required when using inside the boundaries of the airports and with a mandatory requirement for a Listen Before Talk (LBT) mechanism.
		866 - 868	500 mW ERP		
		866.0 - 867.6	2 W ERP		
		916 - 921	1 W ERP	Channel spacing: 1.2 MHz Center frequencies: 916.2, 917.4, 918.6, 919.8 MHz	
					Additional regulation from March 2011. Under License. It is prohibited to use interrogators outside buildings. Permission to use the radio frequencies by active RFID interrogators and the registration of the active interrogator are required.
Saudi Arabia	OK	865.6 - 867.6	2 W ERP	ETSI	
Senegal	NA				
Serbia	OK	865.6 - 867.6	2 W ERP	ETSI	
Singapore	OK	866 - 869	0.5 W ERP		
		920 - 925	2 W ERP		
Slovak Republic	OK	865.6 - 867.6	2 W ERP	ETSI	
Slovenia	OK	865.6 - 867.6	2 W ERP	ETSI	
South Africa	OK	865.6 - 867.6	2 W ERP	ETSI	
		915.4 - 919	4 W EIRP	FHSS	
		919.2 - 921	4 W EIRP	Non-modulating	
Spain	OK	865.6 - 867.6	2 W ERP	ETSI	
Sri Lanka	NA				
Sudan	NA				
Sweden	OK	865.6 - 867.6	2 W ERP	ETSI	
Switzerland	OK	865.6 - 867.6	2 W ERP	ETSI	
Syrian Arab Rep.	NA				

Datum	22.10.13
Projektnr.	
Sachbearb.	Daniel Lenhardt
Seite	5

Country	Status	Frequency in MHz	Power	Technique	Comments
Taiwan	OK	922 - 928	1 W ERP	FHSS	Indoor
		922 - 928	0.5 W ERP		Outdoor
Tajikistan	NA				
Tanzania	NA				
Thailand	OK	920 - 925	4 W EIRP	FHSS	New regulations effective since 20 January 2006. License required for power above 0.5 W.
Trinidad and Tobago	NA				
Tunisia	OK	865.6 - 867.6	2 W ERP	ETSI	
Turkey	OK	865.6 - 867.6	2 W ERP	ETSI	Indoor use only
Turkmenistan	NA				
Uganda	NA				
Ukraine	NA				
United Arab Emirates	OK	865.6 - 867.6	2 W ERP	ETSI	
United Kingdom	OK	865.6 - 867.6	2 W ERP	ETSI	
United States	OK	902 - 928	4 W EIRP	FHSS	
Uruguay	OK	902 - 928	4 W EIRP	FHSS	
Uzbekistan	NA				
Venezuela, RB	OK	902 - 928	4 W EIRP	FHSS	
Vietnam	OK	866 - 869	0.5 W ERP	Licence required for power above 0.5 W ERP Licence required for power above 0.5 W ERP	
		920 - 925	2 W ERP		
Yemen, Rep.	NA				
Zimbabwe	NA				